

# Rodrunner™

*You walk while it works!*

The Rodrunner offers all the features that contractors like in a sectional sewer cleaner – light weight, high speed cable rotation, and short, quick-coupling cables.

## Two Way Operation

Most often, you set the Rodrunner up close to the drain opening. However, on easier jobs where you have some working room, you can run the machine “lawn-mower” fashion, standing behind the machine and keeping the cable taut as it screws into the line.

For close-up work, the wheel brake is set, the power switch is placed next to the machine to be used as a foot switch, and the cable guide hose is attached. Now, the Rodrunner is ready to handle the toughest stoppages in 3-10" lines, as far as 200 feet away.

A heavy-duty 3/4 hp motor with capacitor and overload protection spins cable at 485 rpm, an ideal speed for self-feeding into the line while protecting the cable against sudden torque build-ups. For additional protection, the Rodrunner has an adjustable slip clutch, which is factory set at 100 inch pounds. An optional set of jaws (R-R10AD) enables the Rodrunner to drive 15 ft. x 7/8" (15R10) cables to clear smaller lines.



### TWO WAY CHUCK HANDLE

Locked down against cable, you have both hands free to hold the cable. This is a real help when pulling cable out of the line.

**The toughest tools down the line.™**

**General** / **General Wire Spring Co.**  
**PIPE CLEANERS**

1101 Thompson Avenue • McKees Rocks, PA 15136 USA  
800-245-6200 or 412-771-6300 • Fax: 412-771-2771  
www.drainbrain.com • e-mail: info@drainbrain.com

© General Wire Spring 2001

Continued next page

# Rodrunner™



## CABLE FEEDING TOOL

It gets cable around tight bends, when self feeding cable into line. Ten foot cord on power switch permits remote control.

## FOLDING HANDLE

Rodrunner weighs less than 100 lbs., so it's easy to move to and from the job. Folding handle gives a low profile for more convenient storage on truck.



## QUICK CHUCK ADJUSTMENT

By turning knurled knob, you can adjust the two-way chuck handle so it grips cable like a clamp, or so it disengages as soon as you let go of the handle.



## PNEUMATIC POWER SWITCH

Power switch is located on handle for storage and use in "walk-in" operation. For close-up work, it's removed from handle for use as a foot switch.

## SECTIONAL CABLES



Flexichain with "G" Connector



Proflex with "L" Connector

Ten foot "Cable Saver" sections for the Rodrunner come in the all purpose Flexichain which has a chain center, and a stiffer Proflex which has a spring center.

## SPECIFICATIONS:

### Weight:

90 lbs. (41 kg)

### Dimensions:

22" wide x 19" high with handle folded down.  
(56 cm x 48 cm)

### Motor:

Heavy-duty 3/4 hp with capacitor and 20 ft. power cord rotates cables at 485 rpm. Optional 1 hp motor rotates cables at 400 rpm. Equipped with ground fault circuit interrupter.

### Wheels:

10" rear wheels, 5" caster wheel.

### Wheel Brake:

Locks rear wheels in place or releases them in an instant.

### Combination Hand or Foot Operated Power Switch:

Air activated for safety; no electrical connection between motor and switch; can be used as hand or foot switch. Ten foot air hose.

### Twin V-Belts:

For better power transmission.

### Safety Clutch:

An adjustable spring-loaded clutch is mounted at the rear of the cable drive shaft. Accessible without removing machine housing.

### Chuck Handle:

Clamps on cable or acts as "dead-man's throttle."

### Cable Counter:

Manually operated, to record number of cables in line.

### Rear Cable Guide Hose:

To limit cable whipping behind machine.

### Folding Handle:

Reduces truck storage space.

### Cutter Set:

Spear Head, Hook Auger, 2" U-Cutter, 3" Heavy Duty Side Cutter, 3" Heavy Duty Saw Blade, 4" Rotary Saw Blade, Large Retrieving Tool, Coupling Wrench.

**The toughest tools down the line.™**

**General** / **General Wire Spring Co.**  
**PIPE CLEANERS**  
1101 Thompson Avenue • McKees Rocks, PA 15136 USA  
800-245-6200 or 412-771-6300 • Fax: 412-771-2771  
www.drainbrain.com • e-mail: info@drainbrain.com